



Model

GID-M70T

Mobile phone and wireless data improvement antenna

- 450mm

All networks

4G LTE

704-748 MHz

5.1 dBi Gain

- ➔ Ground independent.
- ➔ Mounts to any bracket with minimum 10mm diameter hole.
- ➔ 4.5 metres RG58 low loss stranded cable.
- ➔ FME female connector fitted.
- ➔ 5 watts maximum input power.

INSTALLATION GUIDE

www.zcg.com.au

ANTENNA DESCRIPTION

The GID-M70T ground independent mobile phone/wireless data antenna is just 450mm tall and delivers excellent performance with 5.1 dBi gain.

This antenna is a rugged, lightweight and unobtrusive design with detachable stainless steel black powder coated whip.

4.5 metres of RG58 low loss stranded cable bottom exits through the base. An FME female connector is fitted to the cable for easy installation as standard, or specify requirements.

A detailed specification sheet is available to download from www.zcg.com.au

TUNING

The antenna has been tuned in the factory to cover all networks 4G LTE mobile phone network.

VSWR has been optimised to better than 1.6:1 across the full frequency range 704 to 748 MHz.

This tuning cannot be altered.

SELECTING THE MOUNTING POSITION

No metal ground plane is necessary for the antenna to operate effectively.

Typical mounting positions for this antenna are to your vehicle bull bar, guard, boot or truck mirror using the appropriate bracket with a minimum 10mm diameter hole.

The antenna can also be mounted in locations other than on a vehicle.

To achieve best performance from your antenna, these are the important principles you should consider when selecting the mounting point :

1. **Mount the antenna in as high a place as possible.**
2. **Mount the antenna as far away from other antennas and metallic objects as possible to avoid distortion of the 360° omnidirectional pattern and interference. At least 350 mm side clearance is desirable, preferably more.**
3. **Mount the antenna vertical, not at an angle.**

INSTALLATION GUIDE

Remove the split nut from the threaded base, remove from the cable. Pass the cable through the hole of your mounting bracket.

Once cable ran, place the split nut back on the cable and onto the threaded base.

From underneath, tighten the nut to secure the antenna firmly to the bracket.

IMPORTANT : *Leave some slack in the cable at the point where the cable bottom exits the threaded base so as not to place unnecessary tension on the cable.*

Route the RG58 cable carefully to your mobile phone. Ensure that the cable is not stretched excessively and there are no sharp kinks. Avoid high heat areas in the engine bay.

Use cable ties, but do not pull so tight as to crush the cable. A damaged feeder cable is a cause of high VSWR and reduced performance.

Insert the FME female connector into your mobile phone or device. The maximum input power rating is 5 watts.

Installation is now complete.



The cable may be cut shorter if desired. However, a new connector will then need to be fitted using proper tools.

If the FME female connector fitted to the cable does not suit your mobile phone, then any other connector which is suitable for RG58 cable can be fitted upon request to ZCG.

Alternatively use a suitable adaptor, or a patch lead.